



Technical Report

Security Hardening Guide for NetApp ONTAP 9

Guidelines for Secure Deployment of ONTAP 9

Product Security Team, NetApp
March 2018 | TR-4569

Abstract

This guide addresses the NetApp® ONTAP® 9 data management software solution. The ONTAP solution unifies the storage infrastructure, often referred to as the NetApp Data Fabric. In addition, the ONTAP solution allows an organization to combine traditional data centers and new architectures into a unified Data Fabric. This approach allows organizations to move, store, and manage data across flash, disk, and cloud resources in a unified manner. The guidance and configuration settings in this document are designed to help organizations meet prescribed security objectives for information system confidentiality, integrity, and availability.

TABLE OF CONTENTS

1	Introduction	4
2	Local Storage Administrator Accounts	4
2.1	Roles, Applications, and Authentication	4
2.2	Default Administrative Accounts	7
2.3	Login and Password Parameters	9
3	System Administration Methods	12
3.1	Command-Line Access	12
3.2	Web Access	14
4	Storage Administrative System Auditing	15
4.1	Sending Out Syslog	15
4.2	Event Notification	16
5	Storage Encryption	17
6	Managing TLS and SSL	18
7	Online Certificate Status Protocol	18
8	Managing SSHv2	19
9	AutoSupport	20
10	NAS File System Local Accounts (CIFS Workgroup)	21
11	NAS File System Auditing	21
12	CIFS SMB Signing and Sealing	22
13	Securing NFS	23
14	Kerberos 5 and Krb5p	24
15	Lightweight Directory Access Protocol Signing and Sealing	24
16	FPolicy	25
16.1	Filtering Controls	26
16.2	Async Resiliency	26

17	Securing Protocols and Ports	26
	Security Resources	29
	References.....	29
	Version History	30

LIST OF TABLES

Table 1) Predefined roles for cluster administrators.	4
Table 2) Predefined roles for SVM administrators.	5
Table 3) Authentication methods.	7
Table 4) Restrictions for management utility user accounts.	10
Table 5) Login banner parameters.	12
Table 6) MOTD parameters.....	13
Table 7) Supported ciphers and key exchanges.	19
Table 8) Rules for access-level parameters in export rules.	23
Table 9) Rules for access parameter outcomes.	24
Table 10) Commonly used protocols and ports.	26
Table 11) NetApp internal ports.....	27

1 Introduction

The evolution of the current threat landscape presents an organization with unique challenges for protecting its most valuable assets: data and information. The advanced and dynamic threats and vulnerabilities we face are ever increasing in sophistication. Coupled with an increase in the effectiveness of obfuscation and reconnaissance techniques on the part of potential intruders, system managers must address the security of data and information in a proactive manner. This guide seeks to assist operators and administrators in that task by leveraging the confidentiality, integrity, and availability integral to the NetApp solution.

2 Local Storage Administrator Accounts

2.1 Roles, Applications, and Authentication

Roles

With role-based access control (RBAC), users have access to only the systems and options that are required for their job roles and functions. The RBAC solution in ONTAP limits users' administrative access to the level granted for their defined role, which allows administrators to manage users by assigned role. ONTAP provides several predefined roles. Operators and administrators can create, modify, or delete custom access control roles, and they can specify account restrictions for specific roles. Table 1 lists the predefined roles in ONTAP.

Table 1) Predefined roles for cluster administrators.

Cluster Role	Brief Description
admin	Top-level administrative account
autosupport	Used by NetApp AutoSupport® OnDemand technology
backup	Provides access to the <code>vserver services ndmp</code> command directory
read-only	Evokes all <code>show</code> commands and resets its own password
none	Provides no command directory access

Table 2) Predefined roles for SVM administrators.

SVM Role	Capabilities
vsadmin	<ul style="list-style-type: none"> • Managing own user account, local password, and key information • Managing volumes, quotas, qtrees, NetApp Snapshot™ copies, and files • Managing logical unit numbers (LUNs) • Performing NetApp SnapLock® operations, except privileged delete • Configuring the protocols NFS, CIFS, iSCSI, and FC (FCoE included) • Configuring the following services: Domain Name System (DNS), Lightweight Directory Access Protocol (LDAP), and Network Information Service (NIS) • Monitoring jobs • Monitoring network connections and network interface • Monitoring the health of storage virtual machines (SVMs; previously known as Vservers)
vsadmin-volume	<ul style="list-style-type: none"> • Managing own user account, local password, and key information • Managing volumes, quotas, qtrees, Snapshot copies, and files • Managing LUNs • Configuring the following protocols: NFS, CIFS, iSCSI, and FC (FCoE included) • Configuring the following services: DNS, LDAP, and NIS • Monitoring network interface • Monitoring health of SVMs
vsadmin-protocol	<ul style="list-style-type: none"> • Managing own user account local password and key information • Configuring the following protocols: NFS, CIFS, iSCSI, and FC (FCoE included) • Configuring the following services: DNS, LDAP, and NIS • Managing LUNs • Monitoring network interface • Monitoring health of SVMs

SVM Role	Capabilities
vsadmin-backup	<ul style="list-style-type: none"> Managing own user account, local password, and key information Managing Network Data Management Protocol (NDMP) operations Making a restored volume read/write Managing NetApp SnapMirror® relationships and Snapshot copies Viewing volumes and network information
vsadmin-snaplock	<ul style="list-style-type: none"> Managing own user account, local password, and key information Managing volumes, except volume moves Managing quotas, qtrees, Snapshot copies, and files Performing SnapLock operations, including privileged delete Configuring the following protocols: NFS and CIFS Configuring the following services: DNS, LDAP, and NIS Monitoring jobs Monitoring network connections and network interface
vsadmin-readonly	<ul style="list-style-type: none"> Managing own user account, local password, and key information Monitoring health of SVMs Monitoring network interface Viewing volumes and LUNs Viewing services and protocols

Application Methods

The application method specifies the access type of the login method. Possible values include `console`, `http`, `ontapi`, `rsh`, `snmp`, `service-processor`, `ssh`, and `telnet`.

Setting this parameter to `service-processor` grants the user access to the service processor. When this parameter is set to `service-processor`, you must also set the `-authentication-method` parameter to `password` or `password and publickey` because the service processor supports only password authentication or two-factor password and public key authentication. SVM user accounts cannot access the service processor. Therefore, operators and administrators cannot use the `-vserver` parameter when this parameter is set to `service-processor`.

For security reasons, Telnet and Remote Shell (RSH) are disabled by default because NetApp recommends SSH for secure remote access. If there is a requirement or unique need to use Telnet or RSH, they must be enabled.

The `security protocol modify` command modifies the existing clusterwide configuration of RSH and Telnet. Enable RSH and Telnet in the cluster by setting the `enabled` field to `true`.

Authentication Methods

The authentication method parameter specifies the authentication method used for logins. Possible values are listed in Table 3.

Table 3) Authentication methods.

Authentication Method	Description
cert	SSL certificate authentication
community	Simple Network Management Protocol (SNMP) community strings
domain	Active Directory authentication
nsswitch	LDAP or NIS authentication
password	Password
publickey	Public key authentication
usm	SNMP user security model

Starting with ONTAP 9.3, chained two-factor authentication is available for local SSH `admin` accounts using `publickey` and `password` as the two authentication methods. In addition to the `-authentication-method` field in the `security login` command, a new field named `-second-authentication-method` has been added. Public key or password can be specified as either the `-authentication-method` or `-second-authentication-method`. However, during SSH authentication, the order is always public key with partial authentication, followed by the password prompt for full authentication.

```
[sam@centos7 ~]$ ssh ontap9.3.NTAP.LOCAL
Authenticated with partial success.
Password:
cluster1::>
```

Starting with ONTAP 9.4, `nsswitch` may be used as a second authentication method with `publickey`.

2.2 Default Administrative Accounts

There are two default administrative accounts: `admin` and `diag`.

Orphaned accounts are a major security vector that often lead to vulnerabilities, including the escalation of privileges. These are unnecessary and unused accounts that remain in the user account repository. They are primarily default accounts that were never used or for which passwords were never updated or changed. To address this issue, ONTAP supports the removal and renaming of accounts.

Note: ONTAP cannot remove or rename built-in accounts. However, NetApp recommends locking any unneeded built-in accounts with the `lock` command.

Although orphaned accounts are a significant security issue, NetApp strongly recommends testing the effect of removing accounts from the local account repository.

To list the local accounts, use the `security login show` command.

```
cluster1::*> security login show -vserver cluster1

Vserver: cluster1
User/Group Name  Application  Authentication Method  Role Name  Acct Is-Nsswitch
Locked Group
-----
```

```

admin          console    password  admin          no    no
admin          http      password  admin          no    no
admin          ontapi    password  admin          no    no
admin          service-processor password  admin          no    no
admin          ssh       password  admin          no    no
autosupport    console    password  autosupport    no    no
6 entries were displayed.

```

Admin Account

The admin account has the role of admin and is allowed access using all applications.

To completely remove the default admin account, you must first create another admin-level account that uses the console login application.

Note: Doing so might cause some undesired effects. Always test new settings that might affect the security status of the solution on a nonproduction cluster first.

```

cluster1::*> security login create -user-or-group-name NewAdmin -application console -
authentication-method password -vserver cluster1

```

```

cluster1::*> security login show -vserver cluster1

Vserver: cluster1

User/Group Name  Application  Authentication Method  Role Name  Acct Locked  Is-Nsswitch Group
-----
NewAdmin         console     password  admin          no    no
admin            console     password  admin          no    no
admin            http        password  admin          no    no
admin            ontapi      password  admin          no    no
admin            service-processor password  admin          no    no
admin            ssh         password  admin          no    no
autosupport      console     password  autosupport    no    no
7 entries were displayed.

```

After the new admin account is created, test access to that account with the NewAdmin account login. With the NewAdmin login, configure the account to have to same login applications as the default or previous admin account (for example, http, ontapi, service-processor, or ssh). This step makes sure that access control is maintained.

```

cluster1::*> security login create -vserver cluster1 -user-or-group-name NewAdmin -application
ssh -authentication-method password
cluster1::*> security login create -vserver cluster1 -user-or-group-name NewAdmin -application
http -authentication-method password
cluster1::*> security login create -vserver cluster1 -user-or-group-name NewAdmin -application
ontapi -authentication-method password
cluster1::*> security login create -vserver cluster1 -user-or-group-name NewAdmin -application
service-processor -authentication-method password

```

After all functions have been tested, you can disable the admin account for all applications prior to removing it from ONTAP. This step serves as a final test to confirm that there are no lingering functions that rely on the previous admin account.

```

cluster1::*> security login lock -vserver cluster1 -user-or-group-name admin -application *

```

To remove the default admin account and all entries for it, use the following command:

```

cluster1::*> security login delete -vserver cluster1 -user-or-group-name admin -application *
cluster1::*> security login show -vserver cluster1

Vserver: cluster1

User/Group Name  Application  Authentication Method  Role Name  Acct Locked  Is-Nsswitch Group
-----

```



```

-----
NewAdmin      console      password    admin        no          no
NewAdmin      http         password    admin        no          no
NewAdmin      ontapi       password    admin        no          no
NewAdmin      service-processor password    admin        no          no
NewAdmin      ssh         password    admin        no          no
autosupport   console      password    autosupport  no          no
7 entries were displayed.

```

Diag Account

A diagnostic account named `diag` is provided with your storage system. You can use the `diag` account to perform troubleshooting tasks in the `systemshell`. The `diag` account and the `systemshell` are intended for low-level diagnostic purposes only and should be used only with guidance from technical support.

The `diag` account is the only account that can be used to access the `systemshell`, through the `diag` privileged command `systemshell`. Before accessing the `systemshell`, you must set the `diag` account password by using the `security login password` command. You should make use of strong password principles and change the `diag` password on a regular interval. Neither the `diag` account nor the `systemshell` is intended for general administrative purposes.

```

ontap9-tme-8040::> set -privilege diag

Warning: These diagnostic commands are for use by NetApp personnel only.
Do you want to continue? {y|n}: y

ontap9-tme-8040::*> systemshell -node ontap9-tme-8040-01
(system node systemshell)
diag@169.254.185.32's password:

Warning: The system shell provides access to low-level
diagnostic tools that can cause irreparable damage to
the system if not used properly. Use this environment
only when directed to do so by support personnel.

ontap9-tme-8040-01%

```

2.3 Login and Password Parameters

An effective security posture adheres to established organizational policies, guidelines, and any governance or standards that apply to the organization. Examples of these requirements include user name lifetime, password-length requirements, character requirements, and the storage of such accounts. The ONTAP solution provides features and functions to address these security constructs.

New Local Account Features

To support an organization's user account policies, guidelines, or standards, including governances, the following functionality is now supported with ONTAP 9:

Note: Configurable settings are managed by using the security login role `config modify` command.

- Configuring password policies to enforce a minimum number of digits, lowercase characters, or uppercase characters
- Requiring a delay after a failed login attempt
- Defining the account inactive limit
- Expiring a user account
- Displaying a password expiration warning message
- Notification of an invalid login

SHA-512 Support

To enhance password security, ONTAP 9 supports the SHA-2 password hash function and defaults to using SHA-512 for hashing newly created or changed passwords. Operators and administrators can also expire or lock accounts as needed.

Preexisting ONTAP 9 user accounts with unchanged passwords continue to use the MD5 hash function after the upgrade to ONTAP 9.0 or later. However, NetApp strongly recommends that these user accounts migrate to the more secure SHA-512 solution by having users change their passwords.

The password hash functionality enables you to perform the following tasks:

- To display user accounts that match the specified hash function, enter the following commands:

```
cluster1::*> security login show -user-or-group-name NewAdmin -fields hash-function
vserver user-or-group-name application authentication-method hash-function
-----
cluster1 NewAdmin console password sha512
cluster1 NewAdmin ontapi password sha512
cluster1 NewAdmin ssh password sha512
```

- To expire accounts that use a specified hash function (for example, MD5), forcing users to change their passwords upon next login, enter the following commands:

```
cluster1::*> security login expire-password -vserver * -username * -hash-function md5
```

- Lock accounts with passwords that use the specified hash function.

```
cluster1::*> security login lock -vserver * -username * -hash-function md5
```

Password Parameters

The ONTAP solution supports password parameters that address and support organizational policy requirements and guidelines. Table 4 describes the `security login role config show` command, which displays information about the account.

Table 4) Restrictions for management utility user accounts.

Attribute	Description	Default	Range
username-minlength	Minimum user name length required	3	3–16
username-alphanum	User name alphanumeric	disabled	Enabled/disabled
passwd-minlength	Minimum password length required	8	3–64
passwd-alphanum	Password alphanumeric	enabled	Enabled/disabled
passwd-min-special-chars	Minimum number of special characters required in the password	0	0–64
passwd-expiry-time	Password expiration time (in days)	Unlimited, which means the passwords never expire	0–unlimited 0 == expire now
require-initial-passwd-update	Require initial password update on first login	Disabled	Enabled/disabled Changes allowed through console or SSH

Attribute	Description	Default	Range
max-failed-login-attempts	Maximum number of failed attempts	0, do not lock account	
lockout-duration	Maximum lockout period (in days)	The default is 0, which means the account is locked for one day	
disallowed-reuse	Disallow last <i>N</i> passwords	6	Minimum is 6
change-delay	Delay between password changes (in days)	0	
delay-after-failed-login	Delay after each failed login attempt (in seconds)	4	
passwd-min-lowercase-chars	Minimum number of lowercase alphabetic characters required in the password	0, which requires no lowercase characters	0–64
passwd-min-uppercase-chars	Minimum number of uppercase alphabetic characters required	0, which requires no uppercase characters	0–64
passwd-min-digits	Minimum number of digits required in the password	0, which requires no digits	0–64
passwd-expiry-warn-time	Display warning message prior to password expiration (in days)	Unlimited, which means never warn about password expiration	0, which means warn user about password expiration upon every successful login
account-expiry-time	Account expires in <i>N</i> days	Unlimited, which means the accounts never expire	The account expiration time must be greater than the account inactive limit
account-inactive-limit	Maximum duration of inactivity before account expiration (in days)	Unlimited, which means the inactive accounts never expire	The account inactive limit must be less than the account expiration time

```

cluster1::*> security login role config show -vserver cluster1 -role admin

                Vserver: cluster1
                Role Name: admin
                Minimum Username Length Required: 3
                Username Alpha-Numeric: disabled
                Minimum Password Length Required: 8
                Password Alpha-Numeric: enabled
Minimum Number of Special Characters Required in the Password: 0
                Password Expires In (Days): unlimited
                Require Initial Password Update on First Login: disabled
                Maximum Number of Failed Attempts: 0
                Maximum Lockout Period (Days): 0
                Disallow Last 'N' Passwords: 6
                Delay Between Password Changes (Days): 0
                Delay after Each Failed Login Attempt (Secs): 4
Minimum Number of Lowercase Alphabetic Characters Required in the Password: 0

```

```

Minimum Number of Uppercase Alphabetic Characters Required in the Password: 0
Minimum Number of Digits Required in the Password: 0
Display Warning Message Days Prior to Password Expiry (Days): unlimited
Account Expires in (Days): unlimited
Maximum Duration of Inactivity before Account Expiration (Days): unlimited

```

3 System Administration Methods

3.1 Command-Line Access

Establishing secure access to systems is a critical part of maintaining a secure solution. The most common command-line access options are SSH, Telnet, and RSH. Of these, SSH is the most secure, industry-standard best practice for remote command-line access. NetApp highly recommends using SSH for command-line access to the ONTAP solution.

The `security ssh show` command shows the configurations of the SSH key exchange algorithms, ciphers, and MAC algorithms for the cluster and SVMs. Table 7 lists the algorithms and ciphers supported with SSH in the ONTAP solution. The key exchange method uses these algorithms and ciphers to specify how the one-time session keys are generated for encryption and authentication and how server authentication takes place.

```

cluster1::> security ssh show
Vserver      Ciphers      Key Exchange Algorithms      MAC Algorithms
-----
nsadhanacluster-2
                aes256-ctr,  diffie-helman-group-        hmac-sha2-256
                aes192-ctr,  exchange-sha256,           hmac-sha2-512
                aes128-ctr,  ecdh-sha2-nistp384
vs0          aes128-gcm   curve25519-sha256          hmac-sha1
vs1          aes256-ctr,  diffie-hellman-group-      hmac-sha1-96
                aes192-ctr,  exchange-sha256           hmac-sha2-256
                aes128-ctr,  ecdh-sha2-nistp384        hmac-sha2-256-
                3des-cbc,    ecdh-sha2-nistp512        etm
                aes128-gcm   hmac-sha2-512
3 entries were displayed.

```

Login Banners

Login banners allow an organization to present any operators, administrators, and even miscreants with terms and conditions of acceptable use, and they indicate who is permitted access to the system. This approach is helpful for establishing expectations for access and use of the system. The `security login banner modify` command modifies the login banner. The login banner is displayed just before the authentication step during the SSH and console device login process. The banner text must be in double quotes (" "), as shown in the following example. Table 5 lists the login banner parameters.

```

cluster1::> security login banner modify -vserver cluster1 -message "Authorized users ONLY!"

```

Table 5) Login banner parameters.

Parameter	Description
vserver	Use this parameter to specify the SVM with the modified banner. Use the name of the cluster admin SVM to modify the cluster-level message. The cluster-level message is used as the default for data SVMs that do not have a message defined.

Parameter	Description
message	<p>This optional parameter can be used to specify a login banner message. If the cluster has a login banner message set, the cluster login banner is used by all data SVMs as well. Setting a data SVM's login banner overrides the display of the cluster login banner. To reset a data SVM login banner to use the cluster login banner, use this parameter with the value "-."</p> <p>If you use this parameter, the login banner cannot contain newlines (also known as ends of lines [EOLs] or line breaks). To enter a login banner message with newlines, do not specify any parameter. You are prompted to enter the message interactively. Messages entered interactively can contain newlines.</p> <p>Non-ASCII characters must use Unicode UTF-8.</p>
uri	<p>(ftp http)://(hostname IPv4 Address 'IPv6 Address'] is the download URI for the banner message.</p> <p>Use this parameter to specify the URI from which the login banner is downloaded.</p> <p>The message must not exceed 2,048 bytes in length. Non-ASCII characters must be provided as Unicode UTF-8.</p>

Message of the Day

The `security login motd modify` command updates the message of the day (MOTD).

There are two categories of MOTD: the cluster-level MOTD and the data SVM-level MOTD. A user logging in to a data SVM's ClusterShell might see two messages: the cluster-level MOTD followed by the SVM-level MOTD for that SVM.

The cluster administrator can enable or disable the cluster-level MOTD on each SVM individually if needed. If the cluster administrator disables the cluster-level MOTD for an SVM, a user logging in to the SVM does not see the cluster-level message. Only a cluster administrator can enable or disable the cluster-level message.

Table 6) MOTD parameters.

Parameter	Description
vserver	Use this parameter to specify the SVM for which the MOTD is modified. Use the name of the cluster admin SVM to modify the cluster-level message.

Parameter	Description
message	<p>This optional parameter can be used to specify a message. If you use this parameter, the MOTD cannot contain newlines. If you do not specify any parameter other than the <code>-vserver</code> parameter, you are prompted to enter the message interactively. Messages entered interactively can contain newlines. Non-ASCII characters must be provided as Unicode UTF-8. The message can contain dynamically generated content using the following escape sequences:</p> <ul style="list-style-type: none"> • <code>\\</code> – A single backslash character • <code>\b</code> – No output (supported for compatibility with Linux only) • <code>\C</code> – Cluster name • <code>\d</code> – Current date as set on the login node • <code>\t</code> – Current time as set on the login node • <code>\I</code> – Incoming LIF IP address (prints <code>console</code> for a console login) • <code>\l</code> – Login device name (prints <code>console</code> for a console login) • <code>\L</code> – Last login for the user on any node in the cluster • <code>\m</code> – Machine architecture • <code>\n</code> – Node or data SVM name • <code>\N</code> – Name of user logging in • <code>\o</code> – Same as <code>\O</code>. Provided for Linux compatibility. • <code>\O</code> – DNS domain name of the node. Note that the output is dependent on the network configuration and may be empty. • <code>\r</code> – Software release number • <code>\s</code> – Operating system name • <code>\u</code> – Number of active ClusterShell sessions on the local node. For the cluster admin: all ClusterShell users. For the data SVM admin: only active sessions for that data SVM. • <code>\U</code> – Same as <code>\u</code>, but has <code>user</code> or <code>users</code> appended • <code>\v</code> – Effective cluster version string • <code>\W</code> – Active sessions across the cluster for the user logging in (<code>who</code>)

CLI Session Timeout

The default CLI session timeout is 30 minutes. The timeout is important to prevent stale sessions and session piggybacking.

Use the `system timeout show` command to view the current CLI session timeout. To set the timeout value, use the `system timeout modify -timeout <minutes>` command.

3.2 Web Access

OnCommand System Manager

If an ONTAP administrator prefers to use a graphical interface instead of the CLI for accessing and managing a cluster, use NetApp OnCommand® System Manager, which is included with ONTAP as a web service, enabled by default, and accessible by using a browser. Point the browser to the host name if using DNS or the IPv4 or IPv6 address through `https://cluster-management-LIF`.

If the cluster uses a self-signed digital certificate, the browser might display a warning indicating that the certificate is not trusted. You can either acknowledge the risk to continue the access or install a certificate authority (CA) signed digital certificate on the cluster for server authentication.

Starting with ONTAP 9.3, Security Assertion Markup Language (SAML) authentication is an option for OnCommand System Manager.

SAML Authentication for OnCommand System Manager

SAML 2.0 is a widely adopted industry standard that allows any third-party SAML-compliant identity provider (IdP) to perform multifactor authentication (MFA) using mechanisms unique to the IdP of the enterprise's choosing and as a source of single sign-on (SSO).

There are three roles defined in the SAML specification: the principal, the IdP, and the service provider (SP). In the ONTAP implementation, a principal is the cluster administrator gaining access to ONTAP through OnCommand System Manager or OnCommand Unified Manager. The IdP is third-party IdP software from an organization such as Microsoft Active Directory Federated Services (ADFS) or the open-source Shibboleth IdP. The SP is the SAML capability built into ONTAP that is used by OnCommand System Manager or the OnCommand Unified Manager web application.

Unlike the SSH two-factor configuration process, after SAML authentication is activated, OnCommand System Manager or ONTAP service processor access requires all existing administrators to authenticate through the SAML IdP. No changes are required to the cluster user accounts. When SAML authentication is enabled, a new authentication method of `saml` is added to existing users with administrator roles for `http` and `ontapi` applications.

After SAML authentication is enabled, additional new accounts requiring SAML IdP access should be defined in ONTAP with the administrator role and the `saml` authentication method for `http` and `ontapi` applications. If SAML authentication is disabled at some point, these new accounts require the `password` authentication method to be defined with the administrator role for `http` and `ontapi` applications and addition of the `console` application for local ONTAP authentication to OnCommand System Manager.

After the SAML IdP is enabled, the IdP performs authentication for OnCommand System Manager access by using methods available to the IdP, such as Lightweight Directory Access Protocol (LDAP), Active Directory (AD), Kerberos, password, and so on. The methods available are unique to the IdP. It is important that the accounts configured in ONTAP have user IDs that map to the IdP authentication methods.

IdPs that have been validated by NetApp are Microsoft ADFS and open-source Shibboleth IdP.

See [TR-4647: Multifactor Authentication in ONTAP 9.3](#) for more information about MFA for OnCommand System Manager, OnCommand Unified Manager, and SSH.

4 Storage Administrative System Auditing

4.1 Sending Out Syslog

Log and audit information is invaluable to an organization from a support and availability standpoint. In addition, the information and details contained in logs (syslog) and audit reports and outputs are generally of a sensitive nature. To maintain security controls and posture, it is imperative that organizations manage log and audit data in a secure manner.

Offloading of syslog information is necessary for limiting the scope or footprint of a breach to a single system or solution. Therefore, NetApp recommends securely offloading syslog information to a secure storage or retention location.

Create a Log-Forwarding Destination

The `cluster log-forwarding create` command creates log-forwarding destinations for remote logging.

Parameters

Use the following parameters to configure the `cluster log-forwarding create` command:

- **Destination host.** This name is the host name or IPv4 or IPv6 address of the server to which to forward the logs.

```
-destination <Remote InetAddress>
```

- **Destination port.** This port is the port on which the destination server listens.

```
[-port <integer>]
```

- **Log-forwarding protocol.** This protocol is used for sending messages to the destination.

```
[-protocol {udp-unencrypted|tcp-unencrypted|tcp-encrypted}]
```

The log-forwarding protocol can use one of the following values:

- `udp-unencrypted`. User Datagram Protocol with no security.
- `tcp-unencrypted`. Transmission Control Protocol (TCP) with no security.
- `tcp-encrypted`. TCP with Transport Layer Security (TLS).
- **Verify destination server identity.** When this parameter is set to `true`, the identity of the log-forwarding destination is verified by validating its certificate. The value can be set to `true` only when the `tcpencrypted` value is selected in the protocol field.

```
[-verify-server {true|false}]
```

- **Syslog facility.** This value is the syslog facility to use for the forwarded logs.

```
[-facility <Syslog Facility>]
```

- **Skip the connectivity test.** Normally, the `cluster log-forwarding create` command checks that the destination is reachable by sending an Internet Control Message Protocol (ICMP) ping and fails if it is not reachable. Setting this value to `true` bypasses the ping check so that the destination can be configured when it is unreachable.

```
[-force [true]]
```

NetApp recommends using the `cluster log-forwarding` command to force the connection to a `-tcp-encrypted` type.

4.2 Event Notification

Securing the information and data leaving a system is vital to maintaining and managing the system's security posture. The events generated by the ONTAP solution provide a wealth of information about what the solution is encountering, the information processed, and more. The vitality of this data highlights the need to manage and migrate it in a secure manner.

The `event notification create` command sends a new notification of a set of events defined by an event filter to one or more notification destinations. The following examples depict the event notification configuration and the `event notification show` command, which displays the configured event notification filters and destinations.

```
cluster1::> event notification create -filter-name filter1 -destinations
  email_dest,syslog_dest,snmp-traphost

cluster1::> event notification show
```


ID	Filter Name	Destinations
1	filter1	email_dest, syslog_dest, snmp-traphost

5 Storage Encryption

Data-at-rest encryption is important to protect sensitive data in the event of a disk that is stolen, returned, or repurposed.

ONTAP 9 has two Federal Information Processing Standard (FIPS) 140-2-compliant data-at-rest encryption solutions:

- NetApp Storage Encryption (NSE) is a hardware solution that makes use of self-encrypting drives.
- NetApp Volume Encryption (NVE) is a software solution that enables encryption of any data volume on any drive type where it is enabled.

NSE and NVE can make use of either external key management or the onboard key manager (OKM). Use of NSE or NVE does not affect ONTAP storage efficiency features. However, NVE volumes are excluded from aggregate inline dedupe.

The OKM provides a self-contained encryption solution for data at rest with NSE or NVE.

NVE and OKM make use of the ONTAP CryptoMod. CryptoMod is now listed on the CMVP FIPS 140-2 validated modules list. See [FIPS 140-2 Cert# 3072](#).

To begin OKM configuration, use the `security key-manager setup` command, which is used to configure both key management methods supported by ONTAP: OKM and the Key Management Interoperability Protocol (KMIP). KMIP is the external key management option. For onboard key management, this configuration walks the operator or administrator through the passphrase setup and additional parameters for configuring OKM.

A part of the configuration is provided in the following example:

```
cluster1::> security key-manager setup
Welcome to the key manager setup wizard, which will lead you through
the steps to add boot information.

Enter the following commands at any time
"help" or "?" if you want to have a question clarified,
"back" if you want to change your answers to previous questions, and
"exit" if you want to quit the key manager setup wizard. Any changes
you made before typing "exit" will be applied.

Restart the key manager setup wizard with "security key-manager setup". To accept a default
or omit a question, do not enter a value.

Would you like to configure onboard key management? {yes, no} [yes]:
Enter the cluster-wide passphrase for onboard key management. To continue the configuration,
enter the passphrase, otherwise
type "exit":
Re-enter the cluster-wide passphrase:
After configuring onboard key management, save the encrypted configuration data
in a safe location so that you can use it if you need to perform a manual recovery
operation. To view the data, use the "security key-manager backup show" command.
```

Starting with ONTAP 9.4, You can use the `-enable-cc-mode true` option with `security key-manager setup` to require that users enter the passphrase after a reboot.

Starting with ONTAP 9.4, you can use the `secure-purge` feature to nondisruptively “scrub” data on NVE-enabled volumes. Scrubbing data on an encrypted volume ensures that it cannot be recovered from the physical media. The following command securely purges the deleted files on vol1 on SVM vs1:

```
cluster1::> volume encryption secure-purge start -vserver vs1 -volume vol1
```

See the [NetApp Encryption Power Guide](#) for more details about NSE, NVE, OKM, and external KMIP servers.

6 Managing TLS and SSL

Beginning with ONTAP 9, you can enable the FIPS 140-2 compliance mode for clusterwide control plane interfaces. By default, the FIPS 140-2-only mode is disabled. You can enable the FIPS 140-2 compliance mode by setting the `is-fips-enabled` parameter to `true` for the `security config modify` command. You can then use the `security config show` command to confirm the online status.

When FIPS 140-2 compliance is enabled, TLSv1 and SSLv3 are disabled, and only TLSv1.1 and TLSv1.2 remain enabled. ONTAP prevents you from enabling TLSv1 and SSLv3 when FIPS 140-2 compliance is enabled. If you enable FIPS 140-2 and then subsequently disable it, TLSv1 and SSLv3 remain disabled, but TLSv1.2 or both TLSv1.1 and TLSv1.2 remain enabled, depending on the previous configuration.

The `security config modify` command modifies the existing clusterwide security configuration. If you enable the FIPS-compliant mode, the cluster automatically selects only TLS protocols. Use the `-supported-protocols` parameter to include or exclude TLS protocols independently from FIPS mode. By default, FIPS mode is disabled, and ONTAP supports the TLSv1.2, TLSv1.1, and TLSv1 protocols.

For backward compatibility, ONTAP supports adding SSLv3 to the `supported-protocols` list when FIPS mode is disabled. Use the `-supported-ciphers` parameter to configure only the Advanced Encryption Standard (AES) or AES and 3DES. You can also disable weak ciphers such as RC4 by specifying `!RC4`. By default, the supported cipher setting is `ALL:!LOW:!aNULL:!EXP:!eNULL`. This setting means that all supported cipher suites for the protocols are enabled, except for the ones with no authentication, no encryption, no exports, and low-encryption cipher suites. These are suites using 64-bit or 56-bit encryption algorithms.

Select a cipher suite that is available with the corresponding selected protocol. An invalid configuration might cause some functionality to fail to operate properly.

Refer to [OpenSSL ciphers](#) published by the OpenSSL software foundation for the correct cipher string syntax. After modifying the security configuration, reboot all the nodes manually.

Enabling FIPS 140-2 compliance has effects on other systems and communications internal and external to ONTAP 9. NetApp highly recommends testing these settings on a nonproduction system that has console access.

Note: If SSH is used to administer ONTAP 9, then you must use an OpenSSH 5.7 or later client.

7 Online Certificate Status Protocol

Online Certificate Status Protocol (OCSP) enables ONTAP applications that use TLS communications, such as LDAP or TLS, to receive digital certificate status when OCSP is enabled. The application receives a signed response signifying that the certificate requested is good, revoked, or unknown.

OCSP enables determination of the current status of a digital certificate without requiring certificate revocation lists (CRLs).

By default, OCSP certificate status checking is disabled. It can be turned on with the command `security config ocsf enable -app app name`, where the `app name` can be `autosupport`, `audit_log`, `fabricpool`, `ems`, `kmip`, `ldap_ad`, `ldap_nis_namemap`, or `all`. The command requires advanced privilege level.

8 Managing SSHv2

Recommendations

- Use passwords for user sessions.
- Use a public key for machine access.

The `security ssh modify` command replaces the existing configurations of the SSH key exchange algorithms, ciphers, or MAC algorithms for the cluster or an SVM with the configuration settings you specify. Table 7 lists the SSH-supported ciphers and key exchanges in ONTAP.

Table 7) Supported ciphers and key exchanges.

Ciphers	Key Exchange
aes256-ctr	diffie-hellman-group-exchange-sha256 (SHA-2)
aes192-ctr	diffie-hellman-group-exchange-sha1 (SHA-1)
aes128-ctr	diffie-hellman-group14-sha1 (SHA-1)
aes256-cbc	diffie-hellman-group1-sha1 (SHA-1)
aes192-cbc	
aes128-cbc	
aes128-gcm	
aes256-gcm	
3des-cbc	

ONTAP also supports the following types of AES and 3DES symmetric encryptions (also known as ciphers):

- hmac-sha1
- hmac-sha1-96
- hmac-md5
- hmac-md5-96
- hmac-ripemd160
- umac-64
- umac-64
- umac-128
- hmac-sha2-256
- hmac-sha2-512
- hmac-sha1-etm
- hmac-sha1-96-etm
- hmac-sha2-256-etm
- hmac-sha2-512-etm
- hmac-md5-etm
- hmac-md5-96-etm
- hmac-ripemd160-etm

- umac-64-etm
- umac-128-etm

9 AutoSupport

The AutoSupport feature of ONTAP allows you to proactively monitor the health of your system and automatically send messages and details to NetApp technical support, your organization's internal support team, or a support partner. By default, AutoSupport messages to NetApp technical support are enabled when the storage system is configured for the first time. In addition, AutoSupport begins sending messages to NetApp technical support 24 hours after it is enabled. This 24-hour period is configurable. To leverage the communication to an organization's internal support team, the mail host configuration must be completed.

Only the cluster administrator can perform AutoSupport management (configuration). The SVM administrator has no access to AutoSupport. The AutoSupport feature can be disabled. However, NetApp recommends enabling it because AutoSupport helps speed problem identification and resolution should an issue arise on the storage system. By default, the system collects AutoSupport information and stores it locally even if you disable AutoSupport.

For more details regarding AutoSupport messages, including what is contained in the various messages and where different types of messages are sent, see the [NetApp Support portal](#). AutoSupport messages contain sensitive data including, but not limited to, the following items:

- Log files
- Context-sensitive data regarding specific subsystems
- Configuration and status data
- Performance data

AutoSupport supports HTTPS, HTTP, and SMTP for transport protocols. Because of the sensitive nature of AutoSupport messages, NetApp strongly recommends using HTTPS as the default transport protocol for sending AutoSupport messages to NetApp support.

In addition, you should leverage the `system node autosupport modify` command to specify the targets of AutoSupport data (for example, NetApp technical support, an organization's internal operations, or partners). This command also allows you to specify what specific AutoSupport details to send (for example, performance data, log files, and so on).

ONTAP offers a unique solution that protects the privacy of sensitive information by masking or filtering sensitive information with the `-remove-private-data` parameter of the `system node autosupport modify` command. When enabled (set to `true`), this parameter removes, encodes, or masks sensitive data from AutoSupport attachments and headers. Use this parameter to eliminate private data from all AutoSupport messages. Eliminated data includes the following items:

- IP addresses
- MAC addresses
- URIs
- DNS names
- Email addresses
- Port numbers
- Node names
- SVM names
- Cluster names
- Aggregate names

- Volume names
- Junction paths
- Policy names
- User IDs
- Group IDs
- LUNs
- Qtree names

By default, this parameter is disabled (set to `false`). NetApp highly recommends enabling this parameter (set to `true`) in any sensitive environments that require the most robust security posture.

To entirely disable AutoSupport, use the `system node autosupport modify -state disable` command.

10 NAS File System Local Accounts (CIFS Workgroup)

Beginning with ONTAP 9, you can configure a CIFS server in a workgroup with CIFS clients that authenticate to the server by using locally defined users and groups. Workgroup client authentication provides an additional layer of security to the ONTAP solution that is consistent with a traditional domain authentication posture. To configure the CIFS server, use the `vserver cifs create` command. After the CIFS server is created, you can join it to a CIFS domain or join it to a workgroup. To join a workgroup, use the `-workgroup` parameter. Here is an example configuration:

```
cluster1::> vserver cifs create -vserver vs1 -cifs-server CIFSSEVER1 -workgroup
Sales
```

Note: A CIFS server in workgroup mode supports only Windows NT LAN Manager (NTLM) authentication and does not support Kerberos authentication.

NetApp recommends using the NTLM authentication function with CIFS workgroups to maintain your organization's security posture. To validate the CIFS security posture, NetApp recommends using the `vserver cifs session show` command to display numerous posture-related details, including IP information, the authentication mechanism, the protocol version, and the authentication type.

11 NAS File System Auditing

Security requires validation. ONTAP 9 provides increased auditing events and details across the solution. Because NAS file systems occupy an increased footprint in today's threat landscape, audit functions are critical to support visibility. Because of the improved audit capability in ONTAP 9, CIFS audit details are more plentiful than ever. Key details, including the following, are logged with events created:

- File, folder, and share access
- Files created, modified, or deleted
- Successful file read access
- Failed attempts to read or write files
- Folder permission changes

You must enable CIFS auditing to generate auditing events. Use the `vserver audit create` command to create an audit configuration. By default, the audit log uses a rotation method based on size. You can use a time-based rotation option if specified in the Rotation Parameters field. Additional log audit rotation configuration details include the rotation schedule, the rotation limits, the rotation days of the week, and the rotation size. The following text provides an example configuration depicting an audit configuration using a monthly time-based rotation scheduled for all days of the week at 12:30.

```
cluster1::> vserver audit create -vserver vs1 -destination /audit_log -rotate-  
schedule-month all -rotate-schedule-dayofweek all -rotate-schedule-hour 12 -  
rotate-schedule-minute 30
```

The new CIFS audit events are as follows:

- **File share.** Generates an audit event when a CIFS network share is added, modified, or deleted using the related `vserver cifs share` commands.
- **Audit policy change.** Generates an audit event when the audit policy is disabled, enabled, or modified using the related `vserver audit` commands.
- **User account.** Generates an audit event when a local CIFS or UNIX user is created or deleted; a local user account is enabled, disabled, or modified; or a password is reset or changed. This event uses the `vserver cifs users-and-groups local-group` command or the related `vserver services name-service unix-user` command.
- **Security group.** Generates an audit event when a local CIFS or UNIX security group is created or deleted using the `vserver cifs users-and-groups local-group` command or the related `vserver services name-service unix-group` command.
- **Authorization policy change.** Generates an audit event when rights are granted or revoked for a CIFS user or a CIFS group using the `vserver cifs users-and-groups privilege` command.

Note: This functionality is based on the system audit function, which enables an administrator to review what the system is allowing and performing from the perspective of a data user.

12 CIFS SMB Signing and Sealing

A common threat vector for file systems and architectures lies in the SMB protocol. To address this vector, the ONTAP 9 solution uses industry-standard SMB signing and sealing. SMB signing protects the security of the Data Fabric by making sure that traffic between storage systems and clients is not compromised by replay or man-in-the-middle attacks. It does so by verifying that SMB messages have valid signatures.

Although SMB signing is disabled by default in the interest of performance, NetApp highly recommends that you enable it. In addition, the ONTAP solution supports SMB encryption, which is also known as sealing. This approach allows for the secure transport of data on a share-by-share basis. By default, SMB encryption is disabled. However, NetApp recommends that you enable SMB encryption.

LDAP signing and sealing are now supported in SMB 2.0 and later. Signing (protection against tampering) and sealing (encryption) enable secure communication between SVMs and Active Directory servers. Accelerated AES new instructions (Intel AES NI) encryption is now supported in SMB 3.0 and later. Intel AES NI improves on the AES algorithm and accelerates data encryption with supported processor families.

To configure and enable SMB signing, use the `vserver cifs security modify` command and verify that the `-is-signing-required` parameter is set to `true`. See the following example configuration:

```
cluster1::> vserver cifs security modify -vserver vs1 -kerberos-clock-skew 3 -  
kerberos-ticket-age 8 -is-signing-required true
```

To configure and enable SMB sealing and encryption, use the `vserver cifs security modify` command and verify that the `-is-smb-encryption-required` parameter is set to `true`. See the following example configuration:

```
cluster1::> vserver cifs security modify -vserver vs1 -is-smb-encryption-required true  
  
cluster1::> vserver cifs security show -vserver vs1 -fields is-smb-encryption-required  
vserver is-smb-encryption-required
```

```
vs1 true
```

13 Securing NFS

Access control is central to maintaining a secure posture. Therefore, ONTAP uses the export policy feature to limit NFS volume access to clients that match specific parameters. Export policies contain one or more export rules that process each client access request. An export policy is associated with each volume to configure client access to the volume. The result of this process determines whether the client is granted or denied (with a permission-denied message) access to the volume. This process also determines what level of access is provided to the volume.

Note: An export policy with export rules must exist on an SVM for clients to access data. An SVM can contain multiple export policies.

Export rules are the functional elements of an export policy. Export rules match client access requests for a volume against specific parameters you configure to determine how to handle the client access requests. An export policy must contain at least one export rule to allow access to clients. If an export policy contains more than one rule, the rules are processed in the order in which they appear in the export policy. The rule order is dictated by the rule index number. If a rule matches a client, the permissions of that rule are used, and no further rules are processed. If no rules match, the client is denied access.

Export rules determine client access permissions by applying the following criteria:

- The file access protocol used by the client sending the request (for example, NFSv4 or SMB)
- A client identifier (for example, host name or IP address)
- The security type used by the client to authenticate (for example, Kerberos v5, NTLM, or AUTH_SYS)

If a rule specifies multiple criteria, and the client does not match one or more of them, the rule does not apply.

An example export policy contains an export rule with the following parameters:

- `-protocol nfs`
- `-clientmatch 10.1.16.0/255.255.255.0`
- `-rorule any`
- `-rwrule any`

The security type determines which level of access a client receives. The three access levels are read-only, read-write, and superuser (for clients with the user ID 0). Because the access level determined by the security type is evaluated in this order, you must observe the rules listed in Table 8 when constructing access levels.

Table 8) Rules for access-level parameters in export rules.

For a Client to Obtain the Following Access Levels	These Access Parameters Must Match the Client's Security Type
Normal user read-only	Read-only (<code>-rorule</code>)
Normal user read-write	Read-only (<code>-rorule</code>) and read-write (<code>-rwrule</code>)
Superuser read-only	Read-only (<code>-rorule</code>) and <code>-superuser</code>
Superuser read-write	Read-only (<code>-rorule</code>) and read-write (<code>-rwrule</code>) and <code>-superuser</code>

The following are valid security types for each of these three access parameters:

- any
- none
- never

These security types are not valid for use with the `-superuser` parameter:

- krb5
- ntlm
- sys

Table 9 lists the possible outcomes based on a client's security type against the three possible access parameters.

Table 9) Rules for access parameter outcomes.

If the Client's Security Type ...	Then ...
Matches a security type specified in the access parameter.	The client receives access for that level with its own user ID.
Does not match a specified security type, but the access parameter includes the option <code>none</code> .	The client receives access for that level and receives the anonymous user with the user ID specified by the <code>-anon</code> parameter.
Does not match a security type specified, and the access parameter does not include the option <code>none</code> .	The client does not receive any access for that level. Note: This restriction does not apply to the <code>-superuser</code> parameter because this parameter always includes <code>none</code> , even when not specified.

14 Kerberos 5 and Krb5p

Beginning with ONTAP 9, Kerberos 5 authentication with privacy service (krb5p) is supported. The `krb5p` authentication mode is secure, and it protects against data tampering and snooping by using checksums to encrypt all traffic between client and server. The ONTAP solution supports 128-bit and 256-bit AES encryption for Kerberos. The privacy service includes verifying the integrity of the received data, authenticating users, and encrypting data before transmission.

The `krb5p` option is most present in the export policy feature, where it is set as an encryption option. The `krb5p` authentication method can be used as an authentication parameter, as seen in the following text:

```
cluster1::> vserver export-policy check-access -vserver vs1 -client-ip
 10.22.32.42 -volume flex_vol -authentication-method krb5p -protocol nfs3 -access-
type read
```

15 Lightweight Directory Access Protocol Signing and Sealing

Beginning in ONTAP 9, signing and sealing are supported to enable session security on queries to an LDAP server. This approach provides an alternative to LDAP-over-TLS session security.

Signing confirms the integrity of LDAP payload data using secret key technology. Sealing encrypts the LDAP payload data to avoid transmitting sensitive information in clear text. The session security settings on an SVM correspond to those available on the LDAP server. By default, LDAP signing and sealing are disabled. To enable this function, run the `vserver cifs security modify` command with the

`session-security-for-ad-ldap` parameter. See the following list of options for LDAP security functions:

- none (default, no signing or sealing)
- sign (sign LDAP traffic)
- seal (sign and encrypt LDAP traffic)

Note: The sign and seal parameters are cumulative, meaning that if the sign option is used, the outcome is LDAP with signing. However, if the seal option is used, the outcome is both sign and seal. In addition, if a parameter is not specified for this command, the default is `none`.

The following text provides an example configuration:

```
cluster1::> vserver cifs security modify -vserver vs1 -kerberos-clock-skew 3 -
kerberos-ticket-age 8 -session-security-for-ad-ldap seal
```

16 FPolicy

Access control is a key security concept. Indeed, visibility and the ability to respond to file access and file operations are critical for maintaining your security posture. To provide visibility and access control for files, the ONTAP solution uses the FPolicy™ feature. FPolicy is an infrastructure component of the ONTAP solution that allows partner applications to monitor and set file access permissions.

File policies can be set based on file type. FPolicy determines how the storage system handles requests from individual client systems for operations such as create, open, rename, and delete. Beginning with ONTAP 9, the FPolicy file access notification framework is enhanced with filtering controls and resiliency against short network outages.

To leverage the FPolicy feature, the FPolicy policy must first be created with the `vserver fpolicy policy create` command. In addition, use the `-events` parameter if FPolicy is used for visibility and the collection of events. The additional granularity provided by ONTAP allows for filtering and access down to the user name level of control. To control privileges and access with user names, specify the `-privilege-user-name` parameter. The following text provides an example of FPolicy creation:

```
cluster1::> vserver fpolicy policy create -vserver vs1.example.com -policy-name
vs1_pol -events cserver_evt,vle1
-engine native -is-mandatory true -allow-privileged-access no -is-
passthrough-read-enabled false
```

After the FPolicy policy is created, it must be enabled with the `vserver fpolicy enable` command. This command also sets the priority or sequence of the FPolicy entry. The FPolicy sequence is important because, if multiple policies have subscribed to the same file access event, the sequence dictates the order in which access is granted or denied. The following text provides a sample configuration for enabling the FPolicy policy and validating the configuration with the `vserver fpolicy show` command:

```
cluster1::> vserver fpolicy enable -vserver vs2.example.com -policy-name vs2_pol
-sequence-number 5
```

```
cluster1::> vserver fpolicy show
Vserver          Policy Name          Sequence  Status  Engine
-----
vs1.example.com  vs1_pol
vs2.example.com  vs2_pol
external
2 entries were displayed.
```

ONTAP 9 includes the FPolicy enhancements described in the following sections.

16.1 Filtering Controls

New filters are available for SetAttr and for removing notifications on directory activities.

16.2 Async Resiliency

If an FPolicy server operating in asynchronous mode experiences a network outage, FPolicy notifications generated during the outage are stored on the storage node. When the FPolicy server comes back online, it is alerted of the stored notifications and can fetch them from the storage node. The length of time the notifications can be stored during an outage is configurable up to 10 minutes.

17 Securing Protocols and Ports

In addition to performing on-box security operations and functions, the hardening of a solution must also include off-box security mechanisms. Leveraging additional infrastructure devices, such as firewalls, intrusion prevention systems (IPs), and other security devices, for filtering and limiting access to ONTAP is an effective way to establish and maintain a stringent security posture. Table 10 lists the common protocols and ports used in the ONTAP solution. This information is a key component for filtering and limiting access to the environment and its resources.

Table 10) Commonly used protocols and ports.

Service	Port/Protocol	Description
SSH	22/TCP	Secure Shell login
telnet	23/TCP	Remote login
Domain	53/TCP	Domain Name Server
HTTP	80/TCP 80/UDP	HTTP
rpcbind	111/TCP 111/UDP	Remote procedure call
NTP	123/UDP	Network Time Protocol
msrpc	135/UDP	Microsoft Remote Procedure Call
Netbios-name	137/TCP 137/UDP	NetBIOS name service
netbios-ssn	139/TCP	NetBIOS service session
SNMP	161/UDP	Simple Network Management Protocol
HTTPS	443/TCP	Secure HTTP
microsoft-ds	445/TCP	Microsoft directory services
rlzdbase	635/TCP	RLZ Dbase
mount	635/UDP	NFS mount
named	953/UDP	Name daemon

Service	Port/Protocol	Description
NFS	2049/UDP 2049/TCP	NFS server daemon
nrv	2050/TCP	NetApp remote volume protocol
iscsi	3260/TCP	iSCSI target port
Lockd	4045/TCP 4045/UDP	NFS lock daemon
NFS	4046/TCP	NFS mountd protocol
acp-proto	4046/UDP	Accounting protocol
pcnfs	4048/TCP 4048/UDP	PCNFS protocol
rquotad	4049/UDP	NFS rquotad protocol
krb524	4444/UDP	Kerberos 524
acp	5125/UDP 5133/UDP 5144/TCP	Alternate control port for disk
Mdns	5353/UDP	Multicast DNS
HTTPS	5986/UDP	HTTPS port: listening binary protocol
TELNET	8023/TCP	Node-scope Telnet
HTTPS	8443/TCP	7MTT GUI tool through HTTPS
RSH	8514/TCP	Node-scope RSH
KMIP	9877/TCP	KMIP client port (internal local host only)
ndmp	10000/TCP	Network Data Management Protocol
cifs witness port	40001/TCP	CIFS witness port
TLS	50000/TCP	Transport layer security
SSH	65002/TCP	Secure Shell
Iscsi	65200/TCP	ISCSI port
rpc	65456/TCP	Remote procedure call
SSH	65502/TCP	Secure Shell
vsun	65503/TCP	vsun

Table 11) NetApp internal ports.

Port/Protocol	Description
900	NetApp cluster RPC

Port/Protocol	Description
902	NetApp cluster RPC
904	NetApp cluster RPC
905	NetApp cluster RPC
910	NetApp cluster RPC
911	NetApp cluster RPC
913	NetApp cluster RPC
914	NetApp cluster RPC
915	NetApp cluster RPC
918	NetApp cluster RPC
920	NetApp cluster RPC
921	NetApp cluster RPC
924	NetApp cluster RPC
925	NetApp cluster RPC
927	NetApp cluster RPC
928	NetApp cluster RPC
929	NetApp cluster RPC
931	NetApp cluster RPC
932	NetApp cluster RPC
933	NetApp cluster RPC
934	NetApp cluster RPC
935	NetApp cluster RPC
936	NetApp cluster RPC
937	NetApp cluster RPC
939	NetApp cluster RPC
940	NetApp cluster RPC
951	NetApp cluster RPC
954	NetApp cluster RPC
955	NetApp cluster RPC
956	NetApp cluster RPC
958	NetApp cluster RPC
961	NetApp cluster RPC

Port/Protocol	Description
963	NetApp cluster RPC
964	NetApp cluster RPC
966	NetApp cluster RPC
967	NetApp cluster RPC
7810	NetApp cluster RPC
7811	NetApp cluster RPC
7812	NetApp cluster RPC
7813	NetApp cluster RPC
7814	NetApp cluster RPC
7815	NetApp cluster RPC
7816	NetApp cluster RPC
7817	NetApp cluster RPC
7818	NetApp cluster RPC
7819	NetApp cluster RPC
7820	NetApp cluster RPC
7821	NetApp cluster RPC
7822	NetApp cluster RPC
7823	NetApp cluster RPC
7824	NetApp cluster RPC

Security Resources

For information regarding the reporting of vulnerabilities and incidents, NetApp security responses, and customer confidentiality, see the [NetApp security portal](#).

References

The following references were used in this TR:

- [ONTAP 9 Release Notes](#)
- [ONTAP 9 Command Reference](#)
- [Administrator Authentication and RBAC Power Guide](#)
- [TR-4647: Multifactor Authentication in ONTAP 9.3](#)
- [NetApp Encryption Power Guide](#)
- [OPENSSL Ciphers](#)
- [CryptoMod FIPS-140-2 Level 1](#)

Version History

Version	Date	Document Version History
Version 1.0	December 2016	Initial release
Version 1.1	December 2017	Updates for ONTAP 9.2, 9.3, and FIPS-140-2
Version 1.2	March 2018	Updates for 9.4

Refer to the [Interoperability Matrix Tool \(IMT\)](#) on the NetApp Support site to validate that the exact product and feature versions described in this document are supported for your specific environment. The NetApp IMT defines the product components and versions that can be used to construct configurations that are supported by NetApp. Specific results depend on each customer's installation in accordance with published specifications.

Copyright Information

Copyright © 2016–2018 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.